

6 INCH FIRE BELL EST-FB 101-6, 8 & 10



PRODUCT OVERVIEW

EST-FB 101 The product is the fire alarm, a fire alarm device, generally used for more staff in public areas. In the event of an emergency situation is controlled by the alarm controller to trigger an alarm, one for each region under normal circumstances, be used for fire alarms, good warning sound effects.

Fire alarm internally by a 24V DC motor driven by the crankshaft and connecting rod bells, no relays work, work current, high reliability.

Fire alarm for supporting specific products and linkage fire alarm systems, when the system recognizes fire broke out by linkage control equipment to the scene.



Feature and Benefits

1. Merit:

- 1) Appearance, firm structure;
- 2) Easy to install, the typical American installation;
- 3) Has low power consumption, large volume, ring-tones crisp, continuous work extremely long-life characteristics;
- 4) Perfectly configured in a variety of alarm systems.

2. Defect:

- 1) Hearing impaired cannot use or be evacuated

Technical Parameter

Model No.	Diameter	Work voltage	Work current @24VDC	Volume(dB)	Weight	Packing weight	Work environment
EST-FB101 6	6"(150*61mm)	DC12V / DC24V / AC230V	50mA	≥96	0.9kg	20kg(20pcs)	Temperature Range: -10℃ ~ +50℃; Humidity Range: 0%~95%RH
EST-FB101 8	8"(200*61mm)		50mA	≥96	1.3kg	15kg(10pcs)	
EST-FB101 10	10"(250*61mm)		50mA	≥96	1.8kg	20kg(10pcs)	

Wiring

Red Wire	Control Input + (DC 24V+)
Black Wire	Control Input - (DC 24V-)

